

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec.

3 of 31

5

Patent Application of

Bill R. Baker

10

For

**TITLE: COMPOUND PHASE ENCODING FOR PRINTED SERVO PATTERNS**

15 **CROSS-REFERENCE TO RELATED APPLICATIONS**

This application claims priority from U.S. Provisional Patent Application No. 60/447,442 filed Feb. 14, 2003, the entire disclosure of which is incorporated herein by reference, and International Application No. PCT/US 03/41733 filed Dec. 31, 2003.

20

**FEDERALLY SPONSORED RESEARCH**

Not Applicable

**SEQUENCE LISTING OR PROGRAM**

Not Applicable

25

30

35

40

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 4 of 31 |

## BACKGROUND OF THE INVENTION

### 1. Field of the Invention

This invention relates to printing or rapidly transferring fixed servo reference data to surfaces such as those of magnetic storage media and, more particularly, to printing servo data with compound phase patterns that provide absolute position information, that are well suited to commercial data channel chips, and that require relatively little space on the recording surface.

### 2. Description of the prior art

Modern magnetic recording systems have servo information or position markers written in an interleaved fashion on the same surface on which data are recorded. To simplify the system the same head is used to read the user data and the servo information. Various special formats are used for the servo information to enable using measurements and subsequent signal processing to determine the position of the read head relative to the center of the desired data track. A head movement mechanism and servo control system keep the read head close enough to the data track center to assure reliable reading and writing of user data.

Early hard disk systems used a special machine, a servo track writer (STW), e.g. U. S. Patent 5333140, to record the servo information on the disk surface. The STW includes a clamping system to hold the hard disk drive (HDD) in a fixed reference position and an external motor with a laser or optical encoder to accurately move a reference pin that extended into the HDD. The actuator or head positioning mechanism of the HDD is biased against the pin so the write head of the HDD can be placed at any desired radius by moving the external motor according to its encoder system. The STW also includes a clock head that is temporarily placed on a surface of the disk by means of a special aperture in the HDD case. Circuitry of the STW writes a clock signal or timing reference by applying a pattern of write current to the clock head. The clock head reads the timing reference signal as the HDD write head is moved to any desired radius. Since the timing reference is fixed relative to the disk it is possible to write servo patterns of a desired form as function of radius and angle on the disk. Related STW are used for removable media such as the ZIP floppy diskette system manufactured by Iomega Corporation.

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 5 of 31

35 The STW must turn the disk through at least one revolution to write the servo information,  
and another fraction of a revolution is required to move the head to the next radius. Many  
servo patterns use the edges of special bursts or sub elements in the determination of the  
position from the read back signal, so it is necessary to write the servo bursts at radial  
displacements of a fraction of the data track width. Therefore it is usually required to write  
two or more servo tracks for each data track. Since HDDs now have about one hundred  
40 thousand or more data tracks, it may require tens of minutes to write the servo pattern.

Because the enclosure of the HDD is required to have openings for the clock head and for the  
reference pin it is necessary to use the STW in a special clean room to avoid contamination of  
the head-media interface. It is expensive and difficult to maintain the complex STW in such a  
45 clean environment.

A new approach was offered by a "printing" method (Ishida, T., et al., "Printed Media  
Technology for an Effective and Inexpensive Servo Track Writing of HDDs", IEEE Trans.  
Magn., p1875, 2001 and Sugita, R., et al., "A Novel Magnetic Contact Duplication  
50 Technique for Servo-Writing on Magnetic Disks", IEEE Trans. Magn. p2285, 2001). In that  
method the desired servo pattern is replicated in a "master disk" consisting of a silicon  
substrate about one millimeter thick with strips of highly permeable cobalt about one half  
micron thick embedded in the silicon. The face of the master containing the cobalt elements  
is placed in contact with a D.C. erased slave disk. Then a permanent magnet producing an  
55 oppositely directed field is brought close to the back surface of the master and is rotated one  
revolution relative to the master-slave pair. The cobalt elements shield portions of the slave  
disk leaving them in the original D.C. state, but gaps in the cobalt pattern allow the field to  
penetrate. The field is concentrated at the gaps and the increased fringing components reverse  
the magnetization of the adjacent portions of the slave disk. This rapid transfer of the pattern  
60 to the entire surface of the slave disk, or "printing", is done as the last step at the end of a  
conventional disk manufacturing line.

Important feature sizes, typically line widths and the thickness of cobalt elements, have been  
steadily decreasing, but the transition density of printing currently lags that of conventional  
65 write heads. Direct printing of a conventional edge of burst servo pattern resulted in poor  
performance at contemporary data densities, (Ishida, et al., "Demodulation of servo tracking

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 6 of 31

signals printed with a lithographically patterned master disk", *IEEE Trans. Magn.*, Vol. 37, No. 4, Jul., 2001, pp1412-1415 ).

- 70 The conventional Gray codes would provide the absolute radial position, but they are not well suited to the printing process and result in fuzzy transitions at track edges. Unfortunately those codes occupy a large part of the surface, they are not well adapted to the architecture of commercial channel chips, and they require larger variations of widths of lines and spaces. The large variations of feature sizes exacerbate noise sources of the printing process. Proper
- 75 choice of geometry including width and thickness of the cobalt elements and width of the gaps is necessary to assure magnetic switching of the slave medium next to the gaps of the master without saturating the cobalt film to produce "secondary gaps" and consequent writing of spurious pulses or noise ( Saito, A., et al., " Magnetic printing technique for longitudinal thin film media with high coercivity of 6000 Oe", J. Appl. Phys., V 91, p 8688, 2002 and
- 80 Baker, "Tradeoffs for magnetic printing of servo patterns", J. Appl. Phys., p8691, 2002 ).

Therefore it was proposed in US Patent 6304407 to use the printed pattern as a reference system for self-servowriting (SSW). Because the printing method involves several processes such as optical diffraction, diffusion in the photo resist, and shadowing during sputtering of

85 the cobalt, it is difficult to produce square corners or small radii of curvature at the ends of the cobalt lines. Therefore phase methods are used as in U.S. Pat. 3686649 for the position information, and the phase is measured by discrete Fourier transforms (DFT) in the manner of U.S. Patent 5784296. In this method the ends of the bars in the inclined phase elements are excluded from the sample window, and pulses are measured at the long, clean edges of

90 magnetic transitions.

After assembly of the HDD it is removed from the clean room and placed on a self-test rack where it begins its self-servowriting directed by the embedded firmware. Well known self-test methods measure possible pattern eccentricity and any minor errors of the position

95 information for each servo block printed on the disk. Then corrections are applied for subsequent writing of a final servo pattern. The relatively low additional cost of printing one surface of a disk eliminates the need for an expensive STW and the clean room in which to operate it.

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 7 of 31

100 Mitsubishi Corporation using well-known magneto-optic (MO) techniques subsequently developed an alternate printing method. The same pattern described above is first replicated as a chromium on glass reticle or mask. Such masks are commonly created by photolithography. Opaque features are left as a thin chromium film on a transparent glass substrate. In this case too the slave disk is initially D. C. erased, and the printing magnet  
105 applies a field in the opposite direction. The applied field is a bit lower than the coercivity of the slave so its magnetization is preserved until a laser is flashed through the mask. The brief laser pulse heats areas under gaps of the pattern. The surface temperature of the recording film rises quickly decreasing the local coercivity and allowing the selected regions to switch magnetization directions.

110 This contact magneto-optic method also has limitations due to diffraction and to the difficulty of maintaining the small space between reticle and slave disk and due to reflections between the two. Using an antireflective coating on the reticle is difficult because the energy density of the laser irradiation damages the coating. Some of these problems are ameliorated by a  
115 projection printing demonstration (Wang, L., et al., "Photo thermal patterning on magnetic media", J. Appl. Phys., V 91, p8685, 2002).

As is well known in the disk drive industry the number of servo wedges or position bearing segments of the disk must increase as the track density increase. Drives now have a few  
120 hundred wedges and the trend is toward higher densities. The patterns are made by various processes such as fine scale lithography, which is also used in the manufacture of semiconductors and read-write heads for disk drives.

The SSW process described above utilized early printed disks when the critical feature sizes or printable line and space widths were greater than one micron. There was no absolute  
125 position information, but it was adequate to slowly move the head in small steps along the radial extent of the HDD to write each of the final servo tracks. The relatively large printed reference patterns are simply overwritten after the final pattern has been completed.

It is also well known that fields at the edges of conventional write heads are poorly  
130 controlled, (Van Herk, "Analytical expressions for side fringing response and crosstalk with finite head and track widths", *IEEE Trans. Magn.*, Vol. 13, No. 6, Nov., 1977, pp1764-1766 and Tsang, et al., "Disk-noise induced peak jitters in high density recording", *IEEE Trans. Magn.*, Vol. 29, No. 6, Nov., 1993, pp3975-3977.) Therefore the STW and the SSW method

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 8 of 31

both introduce noise at edges of bursts of conventional final servo patterns. That noise  
 135 becomes a greater problem at extremely high track densities.

## BRIEF SUMMARY OF THE INVENTION

One object of the present invention is to provide convenient absolute position information  
 140 from a printed pattern so the cross track position of a read sensor of a magnetic recording  
 system or other track oriented machine can be verified from only the local data.

Another object of this invention is to improve magnetic printing by reducing variations in  
 feature size and to better match the pattern to the channel chip capabilities.

145 Another objective is to reduce the area required for the printed pattern so that it ~~might~~can be  
 used directly as the final servo pattern without rewriting in a SSW mode.

## BRIEF DESCRIPTION OF THE DRAWINGS

150 FIG. 1 is a diagram of a printed pattern of the prior art.

FIG. 2 is an attempt to print Gray codes according to prior art.

FIG. 3A is a diagram in logical coordinates that defines simple phase encoded position  
 elements of the prior art that are also used in the present invention.

155 FIG. 3B is an example diagram in logical coordinates of fine position and ~~absolute~~  
~~position-phase elements~~ higher order phase elements of the present invention.

FIG. 4A is a diagram of the phase differences of A and B fine elements of Fig. 3B.

FIG. 4B is a diagram of phase variations of the absolute C burst of Fig. 3B.

FIG. 4C is a diagram of phase variations of the absolute D burst of Fig. 3B.

160 FIG. 5 shows phase variations of the C and D bursts vs the cross track position y.

FIG. 6 shows phase variations in an example positional value phase system.

FIG. 7 shows a system with reduced features to improve surface utilization efficiency.

FIG. 8 is a diagram of a machine with a circular reference surface.

## DETAILED DESCRIPTION

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 9 of 31

The invention comprises two or more phase-encoded subsystems combined in a novel manner that provides an absolute position coordinate. The resulting pattern is well suited to available methods for printing servo patterns on magnetic recording media such as disks or linear tapes. The servo pattern can be easily read and decoded using commercial R/W (Read Write) or channels chips. This method can be used as reference for SSW (Self Servo Writing), and it requires much less surface area, so it can also be used as a final servo pattern.

A schematic diagram in logical coordinates of Fig. 1 shows the magnetization distribution of printed patterns of the prior art. The abscissa or horizontal coordinate  $x$  is a down-track coordinate proportional to the time at which the read head encounters an element of the pattern. The ordinate,  $y$ , is a cross-track coordinate which changes as the head moves to a new track. The white background of the diagram corresponds to a "background" state of magnetization directed generally in the longitudinal direction of the tracks, either toward the right or toward the left ( positive or negative  $x$  direction ). The crosshatched pattern elements are regions where the magnetization has been reversed by the printing process.

The head and read channel produce a pulse as the head crosses a transition between the two states of magnetization. The sign of the pulse when the head leaves the background state is opposite that created at the return to the background. The absolute sign of the pulse at exit from the background is not critical to this invention, and most modern read channels can be configured to work with any consistent background state.

For a linear tape system with a linear actuator that moves the read head straight across the tracks, Fig. 1 resembles the magnetization distribution in physical coordinates on the tape.

For a disk drive with a linear actuator the servo pattern of Fig. 1 would map onto a wedge shaped region in physical coordinates so that vertical lines of Fig. 1 would diverge for increasing radius. For a disk with rotary actuator the constant time lines of the servo wedge would also be arcuate as well as diverging for larger radius.

The servo block of the schematic diagram of Fig. 1 comprises elements **10** that are centered relative to the data tracks. Those track centered data include elements for clock synchronizing, certain special flags such as a SAM (Servo Address Mark), an Index and other markers and Gray code bits, **18**, for coarse position information. Conventional edge of burst

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 10 of 31

fine position elements 14 are offset from the track centerlines. The dashed lines suggest boundaries of the user data tracks. Generally the number of lines and spaces in the timing segment 10 would be greater, but this diagram shows the concepts in a greatly simplified form.

Demonstrations of demodulation using this prior art, ( ibid. Ishida ), were made at relatively low track density. The magnetic printing from a permeable film pattern does not work well for Gray codes, 18, where some small regions should be reversed in the middle of the surrounding region of the background magnetization state. During printing an external field is applied in order to switch the regions under the openings of the pattern. However, the magnetic flux tends to stay in the film in large areas such as 18. Flux flows around smaller openings in the film leaving corresponding portions of the slave surface unaffected.

Another problem is that large film areas, required in the usual Gray codes, may become saturated and lose their shielding characteristic. That allows flux to penetrate the film and create unwanted pulses or noise. At large gaps in the film, 16, the fringing field is smaller, and the magnetization may not be completely reversed.

In the prior art special Gray code structures such as Fig. 2 have been studied. In that format every Gray code cell, of length L in the down track direction, is forced to have one line and one space 20. Information is encoded by the presence or absence of a reversal in the intermediate interval extending the width of the track. Unfortunately, the recording at the cross track ends of those information bits is poorly controlled and leads to noisy read back signal. That corresponds to the weakened field and corresponding noise found at the edges of conventional write heads, ( ibid. van Herk, Tsang ). A further difficulty of patterns such as those of Fig. 2 is that channel chips usually are binary based so Gray code cells must contain 2 or 4 subintervals; three subintervals are not usable.

The present invention avoids the problems of Gray codes by using phase encoding methods to provide absolute position information. This information is decoded from signals read at any cross track location. It is not required to accumulate data as the head is moved incrementally from a special reference position such as a crash stop.



235 Fig. 3A illustrates ~~important~~ geometrical details of the simple phase encoding method of the  
prior art as in U.S. Patent 3686649 to Behr. The pattern is composed of lines and spaces of  
magnetization of alternating direction. ~~For most printing methods the~~ The width, w, of such  
lines must be larger than the limit of the fabrication method, ~~and that limit is observed in the~~  
~~present~~ method. The forward sloped lines, 30, and the backward sloped lines, 32, are  
240 arranged periodically in both x and y directions so that the down track period  $\lambda$  is constant in  
the logical coordinates. Generally the ends of such lines are difficult to print so the signal is  
sampled or read over a restricted interval such as A for the forward slanted group of lines.  
That group will be called the A burst in agreement with terms commonly used in servo  
systems for disk drives.

245 A group of backward slanted lines is designated as the B burst in Fig. 3A. In general it is  
convenient, but not necessary, to make the B burst a reflection of the A burst relative to a  
central vertical timing line as shown here. ~~For the given configuration, signals from the A~~  
~~burst and B burst will be one half cycle out of phase. It would be possible to shift one of the~~  
250 ~~bursts by one quarter cycle in the x direction to generate signals that are in quadrature. That~~  
~~is common in systems with only one phase encoded component, and it also occurs here for~~  
~~each burst independently. A particular relation between phases of all bursts at a given value~~  
~~of y can be achieved by physically moving the bursts or by the well known method of adding~~  
~~a burst-specific offset to each measured phase.~~ The preferred method of demodulating the  
255 read back signal uses a channel chip with DFT. The resulting sine and cosine components of  
the Fourier transform are quadrature components for each burst. Simple transformations yield  
traditional phase angles.

Some truncated lines are omitted in the lower part of Fig. 3A to make the geometry more  
260 clear, but generally the elements will fill the entire transverse range of the compound phase  
pattern of the present invention as suggested in Fig. 3B.

The preferred embodiment uses the DFT of the channel chip to obtain the sine and cosine  
transforms of each burst such as A, B, C, and D of Fig. 3B. Other bursts may be added to the  
265 pattern, and many channel chips accommodate six bursts or more. Other methods can be used  
to measure timing delays of the various bursts, but the DFT is readily available. Sophisticated

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec.

12 of 31

channel chips made for tens of millions of disk drives are very cost effective and can also be used for tape systems if they also function at lower frequencies.

- 270 Well known methods are used to compute the phase delay of the signals from each burst relative to the sample clock that is aligned, as usual, with timing features of the first part of the servo pattern. For the example illustrated in Fig. 3B the phase angles of the four bursts would be  $\Phi_A$ ,  $\Phi_B$ ,  $\Phi_C$ , and  $\Phi_D$ .
- 275 It can be seen from Fig. 3A or Fig. 3B that the phase of the A burst will be increased or shifted in the x direction if the read head moves in the y direction. From the antisymmetric geometry it follows that the phase of the B burst decreases by the same magnitude or  $\Phi_A = -\Phi_B$ . Therefore the sensitivity can be doubled by using the difference,  $\Phi_0 = \Phi_A - \Phi_B = 2\Phi_A$ , to measure the cross track motion. For the reflected geometry, The SNR (Signal to Noise
- 280 Ratio) is also increased by about a factor of  $\sqrt{2}$  if the noise sources are independently distributed.

- The period of the symmetric bursts, A and B, of Fig. 3A is twice the height  $h$  of a line in the y direction. However, the phase difference,  $\Phi_0 = \Phi_A - \Phi_B$ , has a period or pitch,  $p_0$ , only
- 285 half as big as shown in Fig. 3B. Generally the phases  $\Phi_A$  and  $\Phi_B$  are computed to lie in the fundamental interval  $0 \leq \Phi < 2\pi$ , and their discontinuities are slightly offset. With no loss of generality a simple test and conditional addition of an offset maps  $\Phi_0$  to two of the fundamental cycles, each corresponding to motion of  $p_0$  in the transverse direction.

- 290 Because of various noise sources in every recording system there may be a small error in the sample clock and that would create an error,  $\delta$ , in each of the phase values. Those errors would cancel in the difference,  $\Phi_0 = \Phi_A - \Phi_B$ , so it also reduces effects of timing jitter. The value of the error can be found from the sum,  $\Phi_S = \Phi_A + \Phi_B = 2\delta$ . This measured error,  $\delta$ , can be used to correct the measured phase of bursts C, D, etc. that immediately follow the
- 295 fundamental A, B pair of bursts.

Bursts C, D, etc., can be made with various pitches or periods in the transverse or y direction, but with the same period,  $\lambda$ , in the down track or x direction. The simple illustrative example of Fig. 3B includes a C burst with transverse pitch  $p_1 = 3p_0$ , where  $p_0$  is the pitch of the

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 13 of 31

300 difference,  $\Phi_0 = \Phi_A - \Phi_B$ . The **D** burst in this example has pitch  $p_2 = 4 p_0$ . It is convenient to make the sample windows of the **A** and **B** bursts equal, but it is generally reasonable to decrease the widths of subsequent bursts used for absolute position determination.

Experience has shown that the phase of such bursts can be measured with errors smaller than  
 305 about one per cent of a cycle of  $2\pi$  radians. Variations of the phases are shown in polar form in Fig. 4 as the head is moved in the **y** direction over a distance about 13 times the pitch  $p_0$  of the fundamental **A**, **B** pair. Fig. 4A shows variation of the fundamental difference,  $\Phi_0 = \Phi_A - \Phi_B$ , and the integral cycles are marked with numbers 0, 1, 2, ..., 12, 13, ... at angle zero. Fig. 4B plots  $\Phi_C$  for the same motion, and numbered markers indicate the phase of the **C**  
 310 bursts at the start of each cycle of the fundamental difference. The pitch of the **C** burst is three times that of the fundamental difference so  $\Phi_C$  advances at one third the rate of  $\Phi_0$ . Similarly Fig. 4C shows  $\Phi_D$  which advances at one fourth the rate of  $\Phi_0$ .

Exaggerated crosshatched sectors in Fig. 4 suggest the errors or uncertainties in each of the  
 315 three phase measurements at positions corresponding to zero phase of the fundamental  $\Phi_0$ . It is sufficient that the error regions of the higher order phases,  $\Phi_C$  and  $\Phi_D$ , do not touch. Then it is always possible to uniquely determine the cycle number of the fundamental phase,  $\Phi_0$ , and hence the absolute position for all fundamental cycles 0 to 11 =  $3 \cdot 4 - 1$ .

320 As in all such measurements it is possible to determine the phase of each burst or pair of bursts only within one revolution. With no loss of generality the phases can be constrained to the interval  $0 \leq \Phi < 2\pi$ . A method to select the appropriate cycle of the fundamental phase is explained by Fig. 5 for the same example of Figs. 3B, 4A, 4B, and 4C. The higher order phases,  $\Phi_C$  and  $\Phi_D$ , are plotted versus the transverse displacement **y** normalized relative to  
 325 the fundamental pitch  $p_0$ . All three phases are equal to zero at the start, but the higher order phases change at their different rates. Challenges occur when the fundamental phase  $\Phi_0$  must jump from a value near 0 to a value near  $2\pi$ . Those jump points are marked by the row of integers, **j**, corresponding to the number of the cycle beginning at that value of the displacement **y**.

330

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec.

14 of 31

At those locations the phase  $\Phi_C$  also jumps from one to the next of its segments of one-third of the fundamental cycle, and  $\Phi_D$  jumps to its next segment of length one-fourth of the fundamental cycle.

As suggested by the crosshatched sectors of Fig. 4, small errors may occur in the measurements, but the ambiguity is resolved by first deciding the value of the fundamental phase  $\Phi_0$  with its possible, small error. If  $\Phi_0$  is found to be zero or slightly larger, then  $\Phi_C$  and  $\Phi_D$  are both chosen to be in the segments corresponding to values of  $y$  just larger than that at the ideal jump point. Cases where  $\Phi_0$  is slightly less than  $2\pi$  results in segment numbers for C and D phases corresponding to  $y$  values just under those at the ideal jump point.

Because the phase angles,  $\Phi$ , are confined to the range  $0 \leq \Phi < 2\pi$  it follows that the integers designating the subintervals are also limited and repeat modulo the number of segments. The number of phase segments for a burst is the ratio of its pitch to the fundamental pitch,  $p_0$ . It is necessary to decode the combinations of segment indices of the C and D bursts in order to find the cycle number of the fundamental A, B difference.

In Fig. 5 the markers indicate the start of each segment, and the rows of integers under the horizontal axis correspond to the segments of  $\Phi_0$ ,  $\Phi_C$ , and  $\Phi_D$  respectively. The index  $k$  for the C burst repeats modulo 3, and index  $m$  for the D burst repeats modulo 4. Because the integers 3 and 4 are relatively prime (have no common factors) the combinations of  $k$  and  $m$  are unique over the first  $3 \times 4 = 12$  fundamental cycles. Therefore each of the first 12  $k$ - $m$  pairs identify a unique fundamental cycle numbered  $j$  where  $j$  is contained in  $[0,1,2,...11]$ . For larger values of  $j$  the  $k$ - $m$  pairs would repeat.

The values of  $k$  and  $m$  are computed from the phase measurements, and then the value of  $j$  can be computed for this example from the following algorithm.

---

#### ALGORITHM 1

---

$$j = M * \text{mod}(k - m + K * M, K) + m$$


---

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec.

15 of 31

365 Here the modulo function **mod** is the remainder obtained by dividing the first integer argument by the second integer argument in parentheses. Algorithm 1 is valid for any two relatively prime numbers **K** and **M** where  $M > K$  and  $\text{mod}(M, K) = 1$ . Those conditions are satisfied by any pair of successive integers, that is, with  $M = K + 1$ , as well as by many other pairs.

370

The following decoding algorithm is valid if  $\text{mod}(M, K) = 2$ :

---

**ALGORITHM 2**

---

$r = \text{mod}(m - k + K, K)$

if  $r = 0$

375  $t = 0$

else if  $r$  is even

$t = K - r/2$

else

$t = (K - r) / 2$

380 end

$j = t * M + m$

---

Additional bursts can be included in the compound phase pattern to extend the length of the unique combinations of the sub indices provided the number of values for each index has no common factor with any other corresponding number. For example  $K = 3, M = 4, N = 5$  would give unique codes **k, m, n** for **j** running from 0 to  $3 * 4 * 5 - 1 = 59$ .

It can be shown that an odd integer and the next two integers have no common factor, so such a triple can be used to form a unique code sequence of length equal to their product. Then the previously described algorithms can be combined to decode the triplets as follows.

390

---

**ALGORITHM 3**

---

**K** is odd

$M = K + 1$

$N = M + 1$

395  $r = N * \text{mod}(m - n + M^2, M) + n$

$s = \text{mod}(r - k + K, K)$

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 16 of 31

if  $s = 0$  $t = 0$ else if  $s$  is even400  $t = K - s / 2$ 

else

 $t = (K - s) / 2$ 

end

 $j = t * M * N + r$ 

405

Some examples of the successive triplets described above are:

	K	M	N	K*M*N
	5	6	7	210
	11	12	13	1716
410	19	20	21	7980
	51	52	53	140556

Many other combinations of relatively prime integers can be found and similar algorithms can be set up to decode the corresponding sets of segment numbers to find the index  $j$  of the fundamental cycle. Then the fraction of the fundamental cycle can be added to compute the transverse coordinate as

415

$$y = (j + \Phi_0 / (2\pi)) * p_0 \quad (1)$$

#### PREFERRED EMBODIMENT

420

The previous methods using relatively prime numbers of sub intervals could be decoded more easily when the numbers of sub intervals were about the same for all higher order bursts. However, errors in measurements of the phase angles are nearly independent of the pitch of the bursts, and that allows use of an encoding method similar to positional number systems such as our conventional decimal notation.

425

As a simple example let the first higher order burst have a pitch  $R$  times ~~greater than~~ the fundamental pitch  $p_0$ . Then  $R$  sub intervals can be accurately identified in each cycle. Let the pitch of the next burst be  $R * R$  times  $p_0$ . For each additional more significant burst let its pitch be  $R$  times that of its predecessor. The  $2\pi$  phase range of each burst can be accurately

430

RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 17 of 31

divided into  $R$  equal phase segments that each identify one cycle of the preceding, less significant burst. If there are  $Q$  of such higher order bursts, and if the segment indices,  $k_q$ , are measured for each burst, with  $0 \leq k_q \leq R - 1$ , then the cross track position,  $y$ , can be computed as

$$y = [ k_{Q-1} * R^{Q-1} + k_{Q-2} * R^{Q-2} + \dots + k_1 * R + k_0 + \Phi_0 / (2 \pi) ] * p_0 \quad (2)$$

This absolute position can be mapped in various ways to define the physical spacing of tracks in the transverse direction. For example, in hard disk systems some heads may function better than others, and regions near the inner radius of a disk may perform differently from regions near the outer radius. The final, physical mapping or track spacing can be adjusted to optimize robustness and capacity of the drive.

Fig. 6 shows a simple example of such phase variations versus transverse coordinate  $y$ . The radix, or ratio  $R$ , is 4 in this case. The servo control computations are often done with a binary computational unit or DSP ( Digital Signal Processor ) operated in integer format. Some calculations such as multiplication and division by  $R$  can be done with simpler shift and add operations if  $R$  is a power of 2.

In Fig. 6 the segment indices are in the rows designated as  $k$ ,  $m$ , and  $n$ , and the index of the fundamental cycle or the integer part of the quantity in square brackets in equation 2 is

$$j = k * 4^2 + m * 4 + n \quad (3)$$

Of course, the number of phase segments could be changed for each burst, and then the position values would not be simple powers of a single ratio  $R$ , as in equation 2, but would be the product of ratios of all lower order bursts.

In any case the ambiguity caused by the usual system noise at each segment boundary is resolved by working from the phase of the fundamental burst upward through each more significant burst, as explained above. That results in a total error no larger than that of the fundamental burst. The decision making process is similar to that commonly used in reading multi-dial meters having separate dials for units, tens, hundreds, etc.

465 For track oriented servo systems the on-track position must be maintained with deviations no greater than a small fraction of the nominal track pitch. Therefore narrower tracks require more servo information blocks, and that reduces the area available for user data or other purposes.

470 The compound phase system of the present invention offers a means, as suggested in Fig. 7, to ameliorate the space requirements for servo information. Some of the servo blocks comprise more elements such as a synchronization segment 60 for a timing PLL ( Phase Locked Loop ), a SAM ( Servo Address Mark ) 62, certain flags 64 for index or other markers, a forward fine burst 30, a backward fine burst 32, and higher order position bursts  
475 70, 72, and 74. Such complete servo blocks can be combined with the user data areas 78 and with abbreviated servo blocks such as those shown comprising only the fine position bursts 30 and 32.

A machine with a circular reference surface 80 is shown in Fig. 8. Radial position on the  
480 circular tracks 82 is derived from servo blocks 84. Signals from the sensor or transducer 86 are analyzed by the signal unit 90. Further processing by the computation unit 92 provides commands to the servo control 88.

Effective disk drive or tape transport control systems may use timing signals recovered from  
485 the servo blocks to regulate the motion of the medium and to synchronize the servo readback clock to the recorded pattern. At start up the information retrieved from the complete servo blocks can be used to initialize the timing systems. When the medium speed is nearly correct then the delay  $\delta$  of the fundamental bursts of the abbreviated blocks can also be used for final tuning of the timing.

490 If this compound phase pattern is used for the final servo information of a disk drive and if the disks are printed before assembly into a drive then the pattern may be slightly eccentric relative to the axis of rotation. Well known self-test methods can be used to measure the eccentricity of the pattern, and the final data tracks can either be computed to form concentric  
495 tracks or the tracks can follow the eccentricity of the printed servo pattern. In either case predictions of the control system can be verified and corrected at each of the fundamental or



RDWD0301-USA App. No. 10/519,440 (Baker) Amend. D Spec. 19 of 31

fine position chevrons. Adding one or more bursts of higher significance to the reduced servo blocks can enhance the robustness or tolerance of the system to minor disturbances.

500 During rapid seek motion an advantage of the positional encoding system is that it is only necessary to decode the more significant bursts of the complete servo blocks. As the transverse seek speed decreases it is easier to decode the less significant bursts, and finally in settling and tracking modes the fundamental or finest bursts are decoded and used in the control system.

505

In addition to the above mentioned examples, various other modifications and alterations may be made without departing from the invention. Accordingly, the above disclosure is not to be considered as limiting and the appended claims are to be interpreted as encompassing the entire spirit and scope of the invention.